

HP LaserJet Pro MFP M426fdn { Specifications }

FUNCTIONS	Print, copy, scan, fax
MULTITASKING SUPPORTED	Yes
FIRST PAGE OUT BLACK (A4, READY)	As fast as 5.6 sec
FIRST PAGE OUT BLACK (A4, SLEEP)	As fast as 8.0 sec
PRINT SPEED BLACK (ISO, A4)	Normal: Up to 38 ppm [1]
FIRST PAGE OUT (READY)	Black: As fast as 5.6 sec [2]
FIRST PAGE OUT (SLEEP)	Black: As fast as 8.0 sec [2]
FIRST COPY OUT	As fast as 7.2 sec
FIRST COPY OUT (SLEEP)	As fast as 9.7 sec
DUTY CYCLE (MONTHLY, A4)	Up to 80,000 pages
RECOMMENDED MONTHLY PAGE VOLUME	750 to 4,000 [3]
PRINT TECHNOLOGY	Laser
PRINT QUALITY BLACK (BEST)	HP FastRes 1200
PRINT LANGUAGES	HP PCL 5, HP PCL 6, HP Postscript Level 3 emulation, direct PDF (v1.7) printing, URF, PCLM, PWG, Native Office
DISPLAY	7.5 cm (3") intuitive touchscreen Colour Graphic Display (CGD)
PROCESSOR SPEED	1200 MHz
AUTOMATIC PAPER SENSOR	No
REPLACEMENT CARTRIDGES	HP 26A Black LaserJet Toner Cartridge (3,100 pages) CF226A; HP 26X Black LaserJet Toner Cartridge (9,000 pages) CF226X
HP EPRINT CAPABILITY	Yes
MOBILE PRINTING CAPABILITY	HP ePrint; Apple AirPrint™; Mopria-certified; Google Cloud Print 2.0; Mobile apps
WIRELESS CAPABILITY	No
CONNECTIVITY, STANDARD	1 Hi-Speed USB 2.0; 1 host USB at rear side; Gigabit Ethernet 10/100/1000BASE-T network; 802.3az(EEE) 802.11b/g/n / 2.4 / 5 GHZ Wi-Fi radio
NETWORK READY	Standard (built-in Gigabit Ethernet)
MINIMUM SYSTEM REQUIREMENTS	Windows 10 (32 & 64-bit), Windows 8/8.1 (32 & 64-bit), Windows 7 (32 & 64-bit): 1 GHz processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port; Windows Vista (32-bit): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port; Windows Server 2008 (64-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (x64) processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port; Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), Windows Server 2008 (32-bit) (SP1 or greater): 1 GHz 32-bit (x86) processor,

1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite, Internet, USB, 1 GB available hard disk space, OS compatible hardware (for OS hardware requirements see <http://www.apple.com>)

COMPATIBLE OPERATING SYSTEMS	Windows OS compatible with In-Box Driver: Windows 10 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 8/8.1 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 7 all 32 & 64-bit editions, Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.); Windows OS compatible with Universal Print Driver (from http://www.HP.com): Windows 10 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 8/8.1 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 7 all 32 & 64-bit editions, Windows Vista all 32 & 64-bit editions (Home Basic, Premium, Professional, etc.); Mac OS (HP print drivers available from http://www.HP.com and Apple Store): OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Mobile OS (In-OS drivers): iOS, Android, Windows 8/8.1/10 RT; Linux OS (In-OS HPLIP, auto install): BOSS (3.0, 5.0), DEBIAN (6.0, 6.0.1, 6.0.2, 6.0.3, 6.0.4, 6.0.5, 6.0.6, 6.0.7, 6.0.8, 6.0.9, 6.0.10, 7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6), FEDORA (17, 18, 19, 20), LINUX MINT (13, 14, 15, 16, 17), SUSE LINUX (12.2, 12.3, 13.1), UBUNTU (10.04, 11.10, 12.04, 12.10, 13.04, 13.10, 14.04, 14.10); Linux OS (In-OS HPLIP, manual install): MANDRIVA LINUX (2010.0, 2011.0), MEPIS (6.0, 6.5, 7.0, 8.0), PCLINUXOS (2006.0, 2006, 2007.0, 2007, 2008.0, 2008, 2009.0, 2009), RED HAT (8.0, 9.0), RED HAT ENTERPRISE LINUX (5.0, 6.0, 7.0), SLACKWARE LINUX (9.0, 9.1, 10.0, 10.1, 10.2, 11, 12, 12.1), GOS (8.04.1), IGOS(1.0), LINPUS LINUX (9.4, 9.5), LINUX FROM SCRATCH (6); Other OS: UNIX [8]
MEMORY	256 MB
MEMORY, MAXIMUM	256 MB
INTERNAL STORAGE	No
PAPER HANDLING INPUT, STANDARD	100-sheet Tray 1, 250-sheet input Tray 2
PAPER HANDLING INPUT, OPTIONAL	Optional third 550-sheet tray
PAPER HANDLING OUTPUT, STANDARD	150-sheet output bin
MAXIMUM OUTPUT CAPACITY (SHEETS)	Up to 150 sheets
DUPLEX PRINTING	Automatic (standard)
MEDIA SIZES SUPPORTED	Tray 1: A4; A5; A6; B5 (JIS); Oficio (216 x 340 mm); 16K (195 x 270 mm); 16K (184 x 260 mm); 16K (197 x 273 mm); Envelope 10; Envelope Monarch; Envelope B5; Envelope C5; Envelope DL; Custom Size; Statement; Tray 2 & Tray 3: A4; A5; A6; B5 (JIS); Oficio (216 x 340 mm); 16K (195 x 270 mm); 16K (184 x 260 mm); 16K (197 x 273 mm); Custom Size; A5-R; B6 (JIS)
MEDIA SIZES, CUSTOM	Tray 1: 76.2 x 127 to 215.9 x 355.6 mm; Tray 2, 3: 104.9 x 148.59 to 215.9 x 355.6 mm
MEDIA TYPES	Paper (plain, EcoEFFICIENT, light, heavy, bond, coloured, letterhead, preprinted, prepunched, recycled, rough), envelopes, labels, transparencies
MEDIA WEIGHT, SUPPORTED	Tray 1: 60 to 175 g/m ² ; Tray 2, optional 550-sheet Tray 3: 60 to 120 g/m ²

MEDIA WEIGHTS, SUPPORTED ADF	60 to 90 g/m ²
SCANNER TYPE	Flatbed, ADF
SCAN RESOLUTION, OPTICAL	Up to 1200 x 1200 dpi
SCAN SIZE (ADF), MAXIMUM	216 x 355.6 mm
SCAN SIZE (ADF), MINIMUM	102 x 152 mm
SCAN SPEED (NORMAL, A4)	Up to 26 ppm/47 ipm (monochrome), up to 21 ppm/30 ipm (colour)
RECOMMENDED MONTHLY SCAN VOLUME	750 to 4,000 [6]
DUPLEX ADF SCANNING	Yes
AUTOMATIC DOCUMENT FEEDER CAPACITY	Standard, 50 sheets
DIGITAL SENDING STANDARD FEATURES	Scan-to-email; Scan-to-network folder; Scan-to-Cloud
FILE FORMAT SUPPORTED	Scan to USB device and scan from the front panel to a network folder both only support: JPG, PDF
SCAN INPUT MODES	For Scan software (included in the box) support: Windows [JPG, RAW(BMP), PDF, TIFF, PNG, RTF] and Mac [JPG, JPG-2000, TIFF, PNG, PDF, searchable PDF, RTF, TXT]; Front-panel scan, copy, email, fax, or file buttons; HP Scan software; User application via TWAIN or WIA
COPY SPEED (NORMAL)	Black: Up to 38 cpm Color: [4]
COPY RESOLUTION (BLACK TEXT)	600 x 600 dpi
COPY RESOLUTION (COLOR TEXT AND GRAPHICS)	600 x 600 dpi
COPY REDUCE / ENLARGE SETTINGS	25 to 400%
COPIES, MAXIMUM	Up to 99 copies
FAXING	Yes
FAX TRANSMISSION SPEED	3 sec per page [7]
FAX MEMORY	4 MB (250 slerexe pages at standard resolution)
FAX RESOLUTION BLACK (BEST)	Up to 300 x 300 dpi (halftone enabled)
FAX SPEED DIALS, MAXIMUM NUMBER	Up to 120 numbers (119 group dials)
FAX BROADCAST LOCATIONS	119 locations
POWER	Input voltage: 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz)
POWER CONSUMPTION	583 watts (print/copy), 9.1 watts (ready), 2.7 watts (sleep), 0.7 watts (Auto-On/Auto-Off, via USB connectivity), 0.1 watts (off) [4]
ENERGY EFFICIENCY	ENERGY STAR® qualified; EPEAT® Silver
BLUE ANGEL COMPLIANT	No; Please refer to the ECI document
OPERATING TEMPERATURE RANGE	15 to 32.5°C
RECOMMENDED OPERATING HUMIDITY RANGE	30 to 70% RH
ACOUSTIC POWER EMISSIONS (READY)	Inaudible [11]
ACOUSTIC PRESSURE EMISSIONS BYSTANDER (ACTIVE, PRINTING)	55 dB(A)
WHAT'S IN THE BOX	HP LaserJet Pro MFP M426fdn; Preinstalled HP 26A Black LaserJet Toner Cartridge (3,100 pages); Getting Started Guide; Setup poster; Support flyer; Warranty guide; Printer

documentation and software on CD-ROM; Power cord;
Phone cord; Built-in duplexer; Built-in fax [13]

CABLE INCLUDED	No, please purchase USB cable separately
SOFTWARE INCLUDED	Windows 7: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Update, HP Device Toolbox, HP Printer Status and Alerts, HP Product Improvement Study, HP Scan App and Driver, Reconfigure your HP Device, Scan to Email Wizard, Scan to Network Folder Wizard, Warranty and Legal Guide, User Guide; Windows 8+: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Scan App and Driver, Warranty and Legal Guide, User Guide, Reconfigure your HP Device; Windows XP, Windows Vista and associated servers: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Scan App and Driver, Warranty and Legal Guide, User Guide; Mac OS: Welcome Screen (directs users to http://www.HP.com or OS App Source for LaserJet Software)
WARRANTY	One-year warranty. Warranty and support options vary by product, country and local legal requirements. Go to http://www.hp.com/support to learn about HP award winning service and support options in your region.