

HP LaserJet Pro MFP M130fw { Specifications }

FUNCTIONS	Print, copy, scan, fax
MULTITASKING SUPPORTED	Yes
FIRST PAGE OUT BLACK (A4, READY)	As fast as 7.6 sec
FIRST PAGE OUT BLACK (A4, SLEEP)	As fast as 8.8 sec
PRINT SPEED BLACK (ISO, A4)	Normal: Up to 22 ppm
FIRST PAGE OUT (READY)	Black: As fast as 7.6 sec
FIRST PAGE OUT (SLEEP)	Black: As fast as 8.8 sec
FIRST COPY OUT	As fast as 7.8 sec
DUTY CYCLE (MONTHLY, A4)	Up to 10,000 pages [9]
RECOMMENDED MONTHLY PAGE VOLUME	150 to 1500 [10]
PRINT TECHNOLOGY	Laser
PRINT QUALITY BLACK (BEST)	Up to 600 x 600 dpi, HP FastRes 1200 (1200 dpi quality)
PRINT LANGUAGES	PCLmS, URF, PWG
DISPLAY	2.7 in touch screen, LCD (color graphics)
PROCESSOR SPEED	600 MHz
AUTOMATIC PAPER SENSOR	No
REPLACEMENT CARTRIDGES	HP 17A Original Black LaserJet Toner Cartridge CF217A(~1600), HP 19A Original LaserJet Imaging Drum CF219A(~12000). [5]
HP EPRINT CAPABILITY	Yes
MOBILE PRINTING CAPABILITY	Apple AirPrint™; HP ePrint; Google Cloud Print 2.0; Mopria-certified; Wi-Fi Direct; HP Smart App [8]
WIRELESS CAPABILITY	Standard (Wi-Fi 802.11b/g/n)
CONNECTIVITY, STANDARD	Hi-Speed USB 2.0 port (device); built-in Fast Ethernet 10/100Base-TX network port; Phone line port (in/out), wireless
CONNECTIVITY, OPTIONAL	No
NETWORK READY	Standard (built-in Ethernet, Wi-Fi 802.11b/g/n)
MINIMUM SYSTEM REQUIREMENTS	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Windows® XP SP3 or higher (32-bit only): any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8 Apple®OS X EI Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9); 1 GB HD; Internet required; USB
COMPATIBLE OPERATING SYSTEMS	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8;

	Windows® XP SP3 or higher (32-bit only); any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Apple® OS X EI Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9), 1 GB HD; Internet required; USB; Linux (For more information, see http://hplipopensource.com/hplip-web/index.html) [18]
MEMORY CARD COMPATIBILITY	No
MEMORY	256 MB
MEMORY, MAXIMUM	256 MB
INTERNAL STORAGE	No
PAPER HANDLING INPUT, STANDARD	150-sheet input tray
PAPER HANDLING INPUT, OPTIONAL	NA
PAPER HANDLING OUTPUT, STANDARD	100-sheet output tray
MAXIMUM OUTPUT CAPACITY (SHEETS)	Up to 100 sheets
DUPLEX PRINTING	Manual duplex
MEDIA SIZES SUPPORTED	A4; A5; A6; B5 (JIS)
MEDIA SIZES, CUSTOM	76 x 127 to 216 x 356 mm
MEDIA TYPES	Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, postcards
MEDIA WEIGHT, SUPPORTED	60 to 163 g/m ²
MEDIA WEIGHTS, SUPPORTED ADF	70 to 90 g/m ²
SCANNER TYPE	ADF, Flatbed
SCAN FILE FORMAT	JPEG, PDF, PNG
SCAN RESOLUTION, OPTICAL	Up to 300 dpi (color and mono, ADF); Up to 600 dpi (color, flatbed); Up to 1200 dpi (mono, flatbed)
SCAN SIZE (ADF), MAXIMUM	215.9 x 297 mm
SCAN SIZE (ADF), MINIMUM	148.5 x 210 mm
SCAN SPEED (NORMAL, A4)	Up to 12 ppm
RECOMMENDED MONTHLY SCAN VOLUME	150 to 1,500 [17]
DUPLEX ADF SCANNING	No
AUTOMATIC DOCUMENT FEEDER CAPACITY	35 sheets
DIGITAL SENDING STANDARD FEATURES	Scan to email; Scan to network folder
FILE FORMAT SUPPORTED	PDF; JPG
SCAN INPUT MODES	Front control panel, scanning via HP LaserJet Scan (Windows®); HP Director (Macintosh) or TWAIN-compliant or WIA-compliant software
COPY SPEED (NORMAL)	Black: Up to 22 cpm Color: [14]
COPY RESOLUTION (BLACK TEXT)	Up to 600 x 600 dpi
COPY REDUCE / ENLARGE SETTINGS	25 to 400%
COPIES, MAXIMUM	Up to 99 copies
FAXING	Yes
FAX TRANSMISSION SPEED	33.6kbps [15]

FAX MEMORY	Up to 1000 pages
FAX RESOLUTION BLACK (BEST)	Up to 300 x 300 dpi (halftone enabled)
FAX SPEED DIALS, MAXIMUM NUMBER	Up to 120 numbers (119 group dials)
FAX BROADCAST LOCATIONS	119
POWER	110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz/50 Hz, 4.8 A; 220-volt input voltage: 220 to 240 VAC (+/- 10%), 60 Hz/50 Hz, 2.8 A
POWER CONSUMPTION	255 watts (active printing), 4.2 watts (ready), 1.0 watts (sleep), 0.7 watts (Auto Off/Wake on USB, enabled at shipment) [2]
ENERGY EFFICIENCY	ENERGY STAR® qualified
BLUE ANGEL COMPLIANT	Yes, Blue Angel DE-UZ 205—only ensured when using Original HP supplies
OPERATING TEMPERATURE RANGE	15 to 32.5°C
RECOMMENDED OPERATING HUMIDITY RANGE	30 to 70% RH
ACOUSTIC POWER EMISSIONS (READY)	2.6 B(A)
ACOUSTIC PRESSURE EMISSIONS BYSTANDER (ACTIVE, PRINTING)	51 dB(A)
WHAT'S IN THE BOX	HP LaserJet Pro MFP M130fw; Introductory HP Black LaserJet Toner Cartridge ~700 pages; HP LaserJet Imaging Drum ~12,000 pages; Power cord; Phone cord; USB cable; Getting started guide; Set up poster; Support flyer; Warranty documents (CN, Indo, AU, Mex, BR, AG); Printer documentation and software on CD-ROM; Errata declaration (some countries) [1] Introductory HP Black LaserJet Toner Cartridge (~700 pages), HP Original LaserJet Imaging Drum (~12,000 pages). Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies
CABLE INCLUDED	Yes, 1 USB; 1 USB PC to Printer (All regions)
SOFTWARE INCLUDED	For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, Online user manuals, HP Printer Assistant, HP Scan Driver, HP Scan Application, HP Fax Driver (4:1 bundle only), HP Fax Application (4:1 bundle only), HP Product Improvement Study; For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Source for LaserJet Software)
WARRANTY	1 Year Limited Warranty (Return to HP/Dealer - Standard Bench Repair)